


I hereby certify that this paper is being deposited with the United States Postal Service as Express Mail in an envelope addressed to: Assistant Commissioner for Patents, Washington, D.C. 20231, on this date.

January 7, 2002
Date


Express Mail Label No.:
EL846222941US

APPLICATION FOR

UNITED STATES LETTERS PATENT

SPECIFICATION

20201011.030702

INVENTOR(s): Takeo OITA

Title of the Invention: SYNCHRONOUS SIGNAL GENERATOR

SYNCHRONOUS SIGNAL GENERATOR

Background of the Invention

Field of the Invention

5 The present invention relates to a synchronous signal generator using a crystal oscillator, and more specifically to a synchronous signal generator for suppressing the jitter (fluctuation of a signal with time) of a synchronous signal.

10

Description of the Related Art

 A synchronous signal generator is known as a pulse generator for controlling a signal with time for a computer, etc. For example, a synchronous signal
15 generator converts the sine wave outputted from a crystal oscillator into a pulse and outputs it. Recently, to ensure the synchronization of a signal, a high precision synchronous signal is demanded, and the synchronous signal generator is requested to reduce
20 the jitter of an output signal.

 FIG. 1 is an explanatory block diagram of a common synchronous signal generator.

 The synchronous signal generator shown in FIG. 1 includes a crystal oscillator 1 and a pulse converter
25 2. The crystal oscillator 1 includes a crystal vibrator

3 and an oscillator circuit unit 4, and forms, for example, a Corpitts type oscillator circuit. The crystal vibrator 3 is configured by, for example, enclosing an AT-cut crystal piece, an exciting electrode formed on the crystal piece, etc., in an airtight container not shown in the attached drawings. An AT-cut crystal piece (crystal vibrator 3) indicates a vibration frequency (resonance frequency) in inverse proportion to its thickness.

Then, the output signal from the crystal oscillator 1 contains a higher harmonic component f_s ($f_2 \sim f_n$) having a multiple of the frequency of the fundamental wave component f_1 as shown in FIG. 2. In this example, the oscillation frequency f of the crystal oscillator 1 is a frequency of a fundamental wave component f_1 of the crystal vibrator 3, and the output waveform is substantially a sine wave output (the output is referred to as sine wave output). However, there is a shift in the frequency value of the crystal vibrator 3 and the crystal oscillator 1, between the fundamental wave component f_1 and the higher harmonic component f_s .

The pulse converter 2 is formed by, for example, a complementary output driver IC, and converts the sine wave output from the crystal oscillator 1 into positive/negative rectangular pulses. Normally, the

sine wave output of the crystal oscillator 1 is amplified by an amplifier 5, and then input into the pulse converter 2.

However, in the synchronous signal generator with the above mentioned configuration, there is the problem of the jitter generated in the output (pulse waveform) by the pulse converter 2.

That is, as shown in FIG. 2, although the sine wave output of the crystal oscillator 1 mainly contains the fundamental wave component f_1 , it also contains the higher harmonic component f_s for even or odd values. Therefore, the sine wave output is not an ideal sine wave that includes only the fundamental wave component f_1 , generates the distortion by the higher harmonic component f_s , and causes the jitter as a result. That is, the smaller the higher harmonic component f_s is to the fundamental wave component f_1 , the closer to the ideal sine wave is the sine wave output of the crystal oscillator 1.

The pulse converter 2 generates a rectangular pulse with the jitter depending on the level of the higher harmonic component f_s of the output sine wave of the crystal oscillator 1. In short, the closer to the ideal sine wave the input sine wave is, that is, the smaller the level of the higher harmonic component

fs is to the fundamental wave component fl, the smaller jitter of the pulse is generated by the pulse converter 2. However, although the oscillation output of the crystal oscillator 1 mainly contains the fundamental wave component fl, it contains not a small amount of higher harmonic component fs. Therefore, there necessarily occurs the problem of the jitter in the output of the pulse converter 2.

Summary of the Invention

The present invention aims at providing a synchronous signal generator for outputting a pulse with the jitter reduced by setting the sine wave output of the crystal oscillator the closest possible to the ideal sine wave.

The synchronous signal generator according to the present invention includes a crystal oscillator unit, a filter unit, and a pulse converter unit.

The crystal oscillator unit oscillates an output signal.

The filter unit converts an output signal from the crystal oscillator unit into a signal set closer to the ideal sine wave, and outputs the resultant signal. The signal is converted such that, for example, the level of the specific frequency component of the output signal

from the crystal oscillator unit can be relatively higher than the levels of the other frequency components.

With the above mentioned configuration, the synchronous signal generator contains a relatively small amount of higher harmonic component in the output of the crystal oscillator unit, thereby outputting a waveform having small distortion, and obtaining a pulse with small jitter.

Additionally, by configuring the above mentioned filter unit by a crystal filter equal to the crystal oscillator unit in cutting angle of a crystal piece, the jitter of an output signal can be reduced.

Brief Description of the Drawings

FIG. 1 is a block diagram of a common synchronous signal generator;

FIG. 2 shows the frequency spectrum for explanation of the problem with the common synchronous signal generator;

FIG. 3 is a block diagram for explanation of the principle of the present invention;

FIG. 4 is a block diagram of the synchronous signal generator according to an embodiment of the present invention;

FIG. 5 is the frequency spectrum according to an embodiment of the present invention; and

FIG. 6 shows the characteristic of the frequency-temperature of the crystal vibrator applied to an embodiment of the present invention.

Description of the Preferred Embodiment

Described below is the basic principle of the present invention.

FIG. 3 is a block diagram showing the synchronous signal generator according to the present invention.

According to the present invention, it is noticed that when the level of the fundamental wave component f_1 in the sine wave output by the crystal oscillator is set relatively higher than the level of the higher harmonic component f_s , the sine wave output becomes closer to the ideal sine wave, and the pulse which is output by the pulse converter indicates reduced jitter.

The synchronous signal generator shown in FIG. 3 comprises a filter unit 13 between a crystal oscillator 11 for outputting a sine wave signal of a specific frequency using crystal and a pulse converter 12 for converting the sine wave signal into a rectangular pulse. It inputs the output of the crystal oscillator 11 into the filter unit 13, removes or attenuates the frequency

component other than the fundamental wave component f_1 , or amplifies only the level of the fundamental wave component f_1 , and then inputs the result into the pulse converter 12.

5 If the filter unit 13 is configured as a band pass filter having the oscillation frequency f as the center frequency f_0 , and the sine wave output from the crystal oscillator 11 is passed through the band pass filter, then a sine wave output is obtained with the higher harmonic component f_s suppressed relative to the
10 fundamental wave component f_1 . The output pulse obtained by converting the sine wave output into a rectangular wave by the pulse converter 12 has a suppressed influence of the higher harmonic component
15 f_s , thereby minimizing the jitter.

 The filter unit 13 of the synchronous signal generator according to the present invention is not limited to a unit for passing a signal of a specific frequency, that is, a filter, but can be anything that
20 sets the level of the specific frequency component of an input signal relatively higher than the levels of other frequency components, and outputs the result. For example, it can be an amplifier for amplifying the level of the fundamental wave component f_1 into a level
25 higher than the levels of the other frequency components

and outputting the resultant signal.

Described below is an embodiment of the synchronous signal generator according to the present invention.

5 FIG. 4 is a block diagram of the synchronous signal generator according to an embodiment of the present invention.

10 In FIG. 4, the component also shown in FIG. 1 is assigned the same reference numeral, and the detailed explanation is omitted in the following descriptions.

 The synchronous signal generator shown in FIG. 1 comprises, as in the configuration shown in FIG. 1, the crystal oscillator 1 having the oscillation frequency f of the synchronous signal generator as the fundamental wave component f_1 , and the pulse converter 2 as the complementary output driver IC for converting sine wave output into positive/negative pulses through the amplifier 5. With the configuration, the crystal oscillator 1 comprises the crystal vibrator 3 and the oscillator circuit unit 4, and the synchronous signal generator in Fig. 4 comprises a crystal filter 6 corresponding to the filter unit 13 shown in FIG. 3 between the crystal oscillator 1 and the pulse converter 2.

25 The crystal filter 6 forms an input/output

10041011.010702

electrode for a crystal piece as enclosed in an airtight container, and outputs only the frequency (regulated band pass frequency) in a regulated area upon receipt of input.

5 The crystal filter 6 has the center frequency f_0 of the regulated band pass frequency equal to the oscillation frequency f . That is, the center frequency f_0 is equal to the frequency of the fundamental wave component f_1 in the sine wave output by the crystal oscillator 1.

10 Furthermore, by setting the crystal filter 6 and the crystal vibrator 3 equal to each other in frequency-temperature characteristic of a crystal piece, the crystal oscillator 1 and the crystal filter 6 have equal frequency-temperature characteristics.

15 For example, by setting the crystal piece of the crystal filter 6 equal to the AC-cut crystal piece in cutting angle, the crystal oscillator 1 can be equal to the crystal filter 6 in frequency-temperature

20 characteristic, thereby allowing the center frequency f_0 to correspond to a change of the frequency of the fundamental wave component f_1 . Otherwise, also using a device equal to the crystal oscillator 1 in temperature characteristic as an external element for determining

25 the center frequency f_0 , for example, a capacitor, etc.,

20201011 11014001

the crystal oscillator 1 can be equal to the crystal filter 6 in frequency-temperature characteristic. Furthermore, a high Q filter can be used for a temperature change.

5 The sine wave output of the crystal oscillator 1 is input into the crystal filter 6 having the center frequency f_0 as a fundamental wave component f_1 .

 The crystal filter 6 passes a wave through the frequency area centering on the oscillation frequency f (fundamental wave component f_1). After the passage, 10 the sine wave output is amplified by the amplifier 5 as described above, input into the pulse converter 2, converted into positive/negative pulses, and output.

 With the configuration as shown in FIG. 4, the sine 15 wave output first passes through the crystal filter 6, then its higher harmonic component f_s is removed, and the fundamental wave component f_1 becomes dominant. That is, as shown in FIG. 5, the sine wave output from the crystal filter 6 has the frequency spectrum with 20 the higher harmonic component f_s furthermore suppressed as compared with the fundamental wave component f_1 than in the case in which the higher harmonic component f_s does not pass the crystal filter 6. Therefore, after the passage through the crystal filter 6, the sine wave 25 output becomes closer to the ideal sine wave having less

distortion by the higher harmonic component f_s .
Therefore, since the pulse converter 2 receives the
ideal sine wave mainly containing the fundamental wave
component f_1 , a pulse is output with low jitter.

5 Therefore, since the synchronous signal generator
as shown in FIG. 4 inputs the sine wave output of the
crystal oscillator 1 into the pulse converter 2 after
passing it through the crystal filter 6 having the center
frequency f_0 equal to the oscillation frequency f , the
10 output sine wave of the crystal oscillator 1 can be
converted into a pulse signal after having the output
sine wave be close to the ideal sine wave, thereby
outputting a pulse having low jitter.

15 Furthermore, according to the present embodiment,
the crystal vibrator 3 and the crystal filter 6 are equal
in cutting angle of a crystal piece. Thus, the crystal
oscillator 1 using the crystal vibrator 3 and the crystal
filter 6 are basically equal in frequency-temperature
characteristic.

20 FIG. 6 shows the frequency-temperature
characteristic of the crystal vibrator.

 In FIG. 6, the frequency-temperature
characteristic indicates a cubic curve having an
inflection point around the ambient temperature (27°C),
25 the maximum value on the low temperature side and the

minimum value on the high temperature side.

The crystal oscillator 1 has the oscillation frequency f depending on the temperature, and the crystal filter 6 also has the center frequency f_0 depending on the temperature. These temperature characteristics depend on the cutting angle of crystal. The crystal oscillator 1 and the crystal filter 6 include other components such as a capacitor, etc. as well as a crystal piece. Since the frequency-temperature characteristics of these components are taken into account, they are not equal in frequency-temperature characteristic although they are equal in cutting angle. However, since their frequency-temperature characteristics largely depend on the cutting angle of a crystal piece in most cases, the crystal oscillator 1 and the crystal filter 6 can be nearly equal in frequency-temperature characteristic by setting an equal cutting angle of a crystal piece for the crystal oscillator 1 and the crystal filter 6.

Thus, the center frequencies f_0 of the crystal oscillator 1 and the oscillation frequency of the crystal filter 6 similarly change with the change in temperature. That is, when the oscillation frequency f (fundamental wave component f_1) changes with temperature, the center frequency f_0 of the crystal

100441011-030700

filter 6 changes correspondingly. Therefore, although the temperature changes, the constant difference in level between the fundamental wave component f_1 and the higher harmonic component f_s can be maintained. As a result, the synchronous signal generator according to the present embodiment can obtain an ideal sine wave although the temperature changes, thereby outputting a pulse with low jitter.

According to the present embodiment, the pulse converter 2 is a complementary driver IC of two-output type for converting an input signal into a positive/negative pulse. However, it can be a single-output IC, etc. for conversion into a single pulse.

Although the oscillation frequency f of the crystal oscillator 1 is defined as the fundamental wave component f_1 as described above, the oscillation frequency f can be another frequency, for example, a frequency three times as high as the fundamental wave component f_1 (frequency of the higher harmonic component f_s (f_3)). However, in this case, if the oscillation frequency f is the frequency of the frequency component f_3 , the center frequency f_0 of the crystal filter 6 also has to be the frequency of the frequency component f_3 .

Although the crystal filter 6 which is set equal

in frequency-temperature characteristic to the filter unit 13 is used for the filter unit 13, the filter unit 13 can have other configurations. For example, the filter unit 13 can be a SAW filter using a surface acoustic wave device.

When the filter unit 13 is configured as a band pass filter, it is designed to be equal in center frequency f_0 to the oscillation frequency f as a nominal frequency (normally at the ambient temperature of 25°C) to suppress the higher harmonic component f_s relative to the oscillation frequency f . Since the jitter is mainly caused by the higher harmonic elements higher than the fundamental frequency, the filter unit 13 can be configured as a low pass filter except the frequency higher than the fundamental frequency f_1 .

Furthermore, by setting the crystal oscillator 1 and the crystal filter 6 equal to each other in cutting angle of crystal piece, substantially the same frequency-temperature characteristic can be obtained in the example above. However, the same frequency-temperature characteristic can also be obtained by providing, for example, a temperature compensation circuit for matching the frequency-temperature characteristics of them and obtaining the same frequency-temperature

10041011.010702

characteristics.

That is, according to the present invention, the sine wave output of the crystal oscillator 1 is designed to obtain a pulse with low jitter by setting the sine wave output of the crystal oscillator 1 closer to the ideal sine wave in the method using a filter, etc., and the synchronous signal generator with an appropriate and flexible change allowed based on the above mentioned concept is in the technical scope of the present invention.

2020.11.01.10.40.11